


# HD7T User Manual





## Packing List


- 1 x HD7T Monitor
- 1 x Pair of Rubber Covers
- 1 x MH-2 Mount
- 1 x User Manual
- 1 x HDMI to HDMI Cable
- 1 x Safety Box
- 1 x Micro HDMI to HDMI Cable
- 1 x Sunshade

## UI Operation Logic

Tap the screen, swipe left or right, cycle through the shortcut function interface and the image setting interface.




(Shortcut Function Interface)



(Main Menu Interface)

## How to get in icon functions

Click the icon to turn on the function; click the icon again to turn off the function.



Long press the icon, the setting interface shows at the bottom.

Click the icon, the setting interface shows at the bottom of the UI.

Hold the icon and slide to enter the shortcut functions menu.

Click the icon to get in the shortcut functions menu.



There are two in the bottom setting interface, which means you can turn to the next page.



Click to return to the previous page.

## 3D LUT Loading and Deleting

Click icon, 3D LUT setting interface shows at the bottom, select , click the 3D LUT file to use the 3D LUT file.

Load the 3D LUT file into the U disk, plug it into the monitor USB port.



Click to enter the corresponding location of the U disk and load the 3D LUT file.

Click , select the 3D LUT file, hold and swipe up, select "Yes" to delete the 3D LUT file.

## Firmware Upgrade

Unzip the firmware package to the root directory of the U disk.

Please make sure not to power off during the upgrade process.

Compatible with USB flash drives in FAT, FAT32, ExFAT and NTFS formats. (FAT32 is recommended)

Please use a U disk with storage capacity below 16G.



Click the icon to get in the firmware upgrade interface, select . Select "Yes" to upgrade the firmware.

## Shortcut Function Icons

	Peaking		Rectangle Crop
	Zebra		HDR(HLG)
	False Color		Check Field
	Luma Waveform		Guides
	RGB Waveform		Cross Hair
	Audio Meters		Grids
	Luma Histogram		Add Shortcut Function
	3D LUT		Delete Shortcut Function

## Bottom Settings Area Icon

HDMI Input Signal Resolution		Backlight
After Date Loading Before/After 3D LUT		Enter the shortcut function selection interface
Off 3D LUT Switch		Enter the shortcut function setting interface

## Main Menu Icon

	Image Setting		3D LUT
	Image and Menu Flip Settings		Volume Setting
	System Setting		View version information and firmware upgrades

## AV IN Port

HD7T has an AV IN port, significantly enhancing operational convenience and device compatibility.

Note: When the AV cable connection is enabled, the following functions: Zebra, False Color, Luma Waveform, RGB Waveform, Audio Meter, Luma Histogram, 3D LUT, and HDR can't be used.

## Power Input

Battery Compatibility	Sony NP-F970/F960/F750/F550
Power	DC 7-24V



### Company Address:

1406, 14th Floor, Block D, Building 3, Cloud Park, Longgang District, Shenzhen, China

### Factory Address:

Building 1, 401, No. 107, Baoye Road, Zhangkengjing Community, Guanhu Street, Longhua District, Shenzhen, China

### Customer Service:

services@portkeys.com

WWW.PORTKEYS.COM